

**This product may be purchased from Connevens Limited secure online store  
at [www.DeafEquipment.co.uk](http://www.DeafEquipment.co.uk)**



**DeafEquipment.co.uk**

Solutions to improve the quality of life




# GLOBE TROTTER POCKET

RC103719 - COMPACT TRAVEL CHARGER



- Includes 4 x 2300mAh Ni-MH AA's
- Full charge in 5 hours
- Intelligent charge control
- World wide Usability

...TRAVEL WITH STYLE



Intelligent control

Batteries  
Charged

1=4  
AA/AAA  
Ni-Cd Ni-MH

Adaptor  
type

Internal  
Switch  
Mode

Usable  
Worldwide



- The GLOBE TROTTER POCKET will charge AAA or AA size batteries, controlled by a microprocessor.
- Due to an intelligent charge control inside, the charger will switch to trickle charge after charging.
- V-MAX technology protects against damage from using with non rechargeable technologies e.g. Alkaline.
- European, UK & US Travel plug adaptors included for charging throughout the world.
- This is a compact charger that fits discreetly into any jacket pocket or hand luggage.
- Will charge both Ni-Cd & Ni-MH technologies.
- Independent cell charging, will charge 1, 2, 3 or 4 batteries of the same type at the same time.



# Technical Specification

<b>INPUT - RATING</b> VOLTAGE AC connector	100 - 240 VAC 50/60Hz - 150mA Foldable AC power pin : US plug Multi-plug support system	
<b>OUTPUT - RATING</b>	AA / AAA 8.0VDC - 500mA	AA / AAA
<b>CHARGING CURRENT</b> AA AAA	500mA +/- 70mA 500mA +/- 70mA	
<b>CHARGING TIMES</b> AA 800mAh Ni-MH AA 1300mAh Ni-MH AA 2100mAh Ni-MH AA 2300mAh Ni-MH AAA 700mAh Ni-MH AAA 900mAh Ni-MH	<b>CHARGING TIMES</b> 1 Hour 45 Minutes 3 Hours 4 Hours 45 Minutes 5 Hours 15 Minutes 1 Hours 30 Minutes 2 Hours	
<b>TRICKLE CURRENT</b> AA AAA	10mA to 30mA 15mA	
<b>END OF CHARGE DETECTION</b> DELTA V	4mV	
<b>CHARGING INDICATOR</b> GREEN ON  GREEN FLASHING RED ON	<b>1 bicolour LED</b> <ul style="list-style-type: none"> <li>• Power on with no battery cell installed</li> <li>• Battery cells charged up, or maximum charging time reached</li> <li>• Charging</li> <li>• Open or insert the battery cell in charging contact</li> <li>• Bad battery connection</li> </ul>	

# Mechanical Specification

ITEM	H/W/D (mm) <small>In Packaging</small>	Weight (g) <small>In Packaging</small>	QTY per pack
GLOBE TROTTER POCKET	201 / 169 / 84	289	1

## BEFORE PLUGGING THE BATTERIES INTO THE MAINS POWER

The batteries should be inserted (take care to observe polarity) in quantities of one to four pieces. Do not mix battery types : charge only Ni-Cd or Ni-MH batteries.

## CHARGE AND END OF CHARGE FOR AAA OR AA SIZE BATTERIES

As the charger is connected to the mains, the charge begins and the charging LED indicator flashes green. The end of charge is automatic. For safety reasons, the charge is also equipped with a safety timer adjusted at 8 hours. When the end of charge is detected, the Green LED will illuminate.

## PROTECTION AGAINST REVERSED CONNECTION

By the design of the charger, when a battery (AAA or AA) is inserted the wrong way, there is no contact between the charger and the battery. That is why the charge does not begin and the LED does not illuminate.

# Logistic Data

ITEM	BARCODE	INNER	Weight (g)	H/W/D (mm)	OUTER	Weight (g)	H/W/D (mm)	Outers/Layer	Layers/pallet
GTP	3 660711 03719 0	6	2000	310/175/215	12	4400	370/320/235	9	3